

Bass - midrange driver

130 mm

MAIN FEATURES :

OVERHUNG MOTOR DESIGN 38 MM TITANIUM VC FORMER SOFT RUBBER SURROUND **VENTED POLE PIECE & SPIDER** 70 HZ - 3 KHZ IN VENTED BOX





A FEA optimized overhung motor design with 38 mm titanium voice coil former guarantees very low energy storage and good heat transfer.


The low loss rubber surround and a thin fabric spider center the moving parts with high linearity.

We recommend a bass - midrange application from 70 Hz - 3000 Hz.











50259 Pulheim





65

6,50





| Overall diameter | 130 | mm |
|--|-----------------------------|----|
| Cutout hole square | 111 | mm |
| Frontplate depth | 6.5 | mn |
| Overall depth | 64.5 | mn |
| Motor assembly diameter | 102 | mn |
| Motor assembly depth | 32 | mn |
| Screw fitting | DIN 7984, 4mm | |
| Terminal | +: 6.3 x 0.8 / -: 6.3 x 0.8 | mn |
| Shipping weight / net weight (one piece) | 2.0 / 1.8 | kg |
| Shipping size (pair) | 180 / 180 / 240 | mn |

| Thiele/Small Parameters | | | |
|--------------------------|-----|-------|-----------------|
| Sensitivity (2.83V / 1m) | Lp | 89.5* | dB |
| DC-resistance | Re | 6.4 | Ohm |
| Resonance frequency | Fs | 72 | Hz |
| Equivalent volume of air | Vas | 5.1 | L |
| Mechanical Q | Qms | 7 | |
| Electrical Q | Qes | 0.52 | |
| Total Q | Qts | 0.48 | |
| Effective piston area | Sd | 83 | cm ² |
| Moving mass | Mms | 9.4 | g |
| Suspension compliance | Cms | 0.52 | mm/N |
| Mechanical resistance | Rms | 0.61 | kg x s |

| Voice Coil data | | | |
|----------------------------|------|----------|-----|
| Power handling | Р | 120* | Wat |
| Linear excursion | Xmax | +/- 4 | mm |
| Voice coil diameter | | 38 | mm |
| Voice coil former material | | Ti | |
| Voice coil material | | Cu | |
| Voice coil inductance | Le | 0.41 | mH |
| Force factor | ВІ | 7.3 | N/A |
| Motor type | | Overhung | |
| Ferrofluid filling | | no | |

^{*} Please refer to www.accuton.com for exact measurement conditions and further information.